### MiniDisc Remote Indicator



## Product overview Product MiniDisc Remote Indicator Part No. 53832-070 Compliance

#### **Product information**

The MiniDisc Remote Indicator is a lightweight compact indicator for use in fire protection systems.

The indicator may be used in all installations incorporating Apollo Detectors including Series 65, AlarmSense, Orbis, XP95, Discovery, Soteria and Intrinsically Safe detectors.

The MiniDisc Remote Indicator is only 20 mm high and 80 mm in diameter. It is made up of two parts - the base which is installed onto a wall or soffit and the lid which is fitted to the base with a bayonet lock.

An anti-tamper screw in the lid locks the unit together..

Two pairs of keyhole fixings are provided - one for  $50\ mm$  and the other for  $60\ mm$  fixing centres.

#### EMC Directive 2014/30/EU

The MiniDisc Remote Indicator complies with the essential requirements of the EMC Directive 2014/30/EU, provided that it is used as described in this datasheet.

A copy of the Declaration of Conformity is available from the Apollo website: www.apollo-fire.co.uk

Conformity of the MiniDisc Remote Indicator with the EMC Directive, does not confer compliance with the directive on any apparatus or systems connected to them.

#### Technical data

All data is supplied subject to change without notice. Specifications are typical at 24V, 25°C and 50% RH unless otherwise stated.

Voltage A and C 5 - 36 V

Max current B and C $25 \text{ mA up to } 40^{\circ}\text{C}$ Operating temperature $-10 ^{\circ}\text{C to } +60 ^{\circ}\text{C}$ 

#### Detector range connections:

Series 65 A and C B and C AlarmSense Orbis A and C Orbis Intrinsically Safe A and C XP95 A and C XP95 Intrinsically Safe B and C Discovery A and C A and C Soteria

Standards and approvals VNIIPO, CNBOP, Kazaksthan

**Dimensions** 80 mm diameter x 20 mm high

Materials White flame-retardant polycarbonate

# MiniDisc remote indicator connections C (-) B (+)

36 Brookside Road, Havant Hampshire, PO9 1JR, UK.

Tel: +44 (0)23 9249 2412 Fax: +44 (0)23 9249 2754 Email: sales@apollo-fire.com Web: www.apollo-fire.co.uk All information in this document is given in good faith but Apollo Fire Detectors Ltd cannot be held responsible for any omissions or errors. The company reserves the right to change the specifications of products at any time and without prior notice.









This page has intentionally been left blank

